



Instructions For the Fastime 6 Stopwatch: 30 lap memory, countdown/up timer, pacer, alarm and time of day/date functions

Stopwatch mode:



Event Timing:

Press **C** – Start, **C** – Stop (time Out). **C** – Continue
C – Stop **A** - Reset

Split Timing:

Top display shows cumulative time to last split.
Middle display shows previous split lap time. Bottom display shows the cumulative running time

Press **C** –Start,

A – Splits,

C – Stop. **A** - Reset

Memory Recall: Press **B** anytime to recall memory.
1st display shows fastest lap number and time. Press **B** again for slowest lap details
Press **B** each split time to show split times starting from the last split. Each display shows the split number, the lap time and cumulative time.
Press **B** to return to current running time

Press **MODE** button to move to Time of Day/date display:

To set time of day and date, Press and hold **B** until digits flash. Press **A** to choose digits to change. Press **C** to change the digits. Press **B** to exit setting

Press **MODE** button to move to Alarm/Time of Day display:

To set alarm time, Press and hold **B** until digits flash. Press **A** to choose digits to change. Press **C** to change the digits. Press **B** to exit setting

Press **MODE** button to move to Pacer display:

Press **A** to set the pacer (from 5 to 240 per minute). Press **C** to start/stop the pacer

Press **MODE** button to move to Countdown/up Timer (9hr 59m 59sec) display:

To set timer, Press and hold **B** until digits flash. Press **A** to choose digits to change. Press **C** to change the digits. Press **B** to exit setting.

To start/stop the timer press **C** **The** timer counts down to zero then counts up until stopped