



Instructions For the Fastime CW1 Compass Wristwatch: digital compass, dual time of day/date, alarm, countdown/up/repeating timer , stopwatch



Press **MODE** button to scroll through function sequence of:
Stopwatch
Alarm
Timer
Second time of day
Time of day date

Press **COMPASS** button anytime to enter compass mode

Compass Calibration:

- i) In compass mode, hold down **RESET/SPLIT** button. "Hold to Cal" is displayed until the "PRESS Start" message shows on the display
- ii) Press **START/STOP** button. The "Turn 2 to Cal" display appears. Turn the watch twice (clockwise) slowly.
- iii) Press **START/STOP** button again to complete the calibration. The "CAL DONE" message will display for about 1second

To set the declination angle:

- i) In compass mode, hold down **RESET/SPLIT** button. "Hold to Cal" is displayed until the "PRESS Start" message shows on the display.
- ii) Press **MODE** button to change to declination setting screen. The digits flash
- iii) Press **MODE** button to move to digits to change.
- iv) Press **START/STOP** button to change direction and degree digits.
- v) Press **RESET/SPLIT** to end calibration process.

Stopwatch Event Timing:

Press **START/STOP** – Start, **START/STOP** – Stop (time Out). **START/STOP**– Continue, **START/STOP** – Stop, **RESET/SPLIT** - Reset

Split Timing:

Press **START/STOP** –Start,

Press **SPLIT/RESET** – Cumulative split.

Press **SPLIT/RESET** - Return to running time **or** Returns to running time after 15 seconds.

Press **START/STOP** –Stop,

Press **SPLIT/RESET** – Reset.

Press **MODE** button to move to Alarm display:

To set alarm time, Press and hold **RESET/SPLIT** until digits flash. Press **MODE** to choose digits to change. Press **START/STOP** to change the digits. Press **RESET/SPLIT** to exit setting

Press **MODE** button to move to Countdown Timer (9hr 59m 59sec) display:

The timer counts down from the preset target time then stops

To set timer, Press and hold **RESET/SPLIT** until digits flash. Press **MODE** to choose digits to change. Press **START/STOP** to change the digits. Press **RESET/SPLIT** to exit setting.

To start/stop the timer press **START/STOP**
the timer counts down to zero then STOPS

Press **MODE** button to move to 2ND Time of Day display:

To set time of day and date, Press and hold **RESET/SPLIT** until digits flash. Press **MODE** to choose digits to change. Press **START/STOP** to change the digits. Press **RESET/SPLIT** to exit setting.

Press **MODE** button to move to Time of Day/date display:

To set time of day and date, Press and hold **RESET/SPLIT** until digits flash. Press **MODE** to choose digits to change. Press **START/STOP** to change the digits. Press **RESET/SPLIT** to exit setting.

